



**NOTES:**

1. A FIFTH TERMINAL (STINGER) IS REQUIRED FOR A 120/208V SERVICE.
2. WIRE SIZE RANGE:
  - 2.1 - 100 AMP SOCKET: LUGS SUITABLE FOR #6 - #2/0 STRANDED CU/AL CONDUCTORS.
  - 2.2 - 200 AMP SOCKET: LUGS SUITABLE FOR #2 - 350 KCMIL CU/AL CONDUCTORS.
3. APPROXIMATE DIMENSIONS:
  - 3.1 - 100 AMP SOCKET: 3-5/16"(D) X 8"(W) X 11-1/2"(H).
  - 3.2 - 200 AMP SOCKET: 4-3/8"(D) X 11"(W) X 15-1/2"(H).
4. CONTACT LEHI CITY POWER FOR AVAILABLE SERVICE VOLTAGES.



**REQUIREMENTS & STANDARDS**  
**METER SOCKET**  
**SINGLE PHASE WIRING DIAGRAM**  
**120/240 VOLT OR 120/208 VOLT**  
**100 - 200 AMP RESIDENTIAL OR COMMERCIAL**

DWG: **6.1.1**  
 REV. 0.00  
 BY: GWK/BT  
 DATE: 4/21/17