



NOTES:

1. A FIFTH TERMINAL (STINGER) IS REQUIRED FOR A 120/208V SERVICE.
2. WIRE SIZE RANGE: LUGS SUITABLE FOR #2 - 350 kcmil Cu/Al CONDUCTORS.
3. APPROXIMATE DIMENSIONS: 5"(D) x 13"(W) x 19"(H).
4. METER SOCKET SHALL HAVE BYPASS. (LINK OR MANUAL)
5. KNOCKOUTS: THREE ON BOTTOM AND ONE EACH ON BOTH SIDES AND BACK; KNOCKOUTS ARE CONCENTRIC TYPE WITH A MAXIMUM DIAMETER OF 3".
6. FOR OVERHEAD SERVICES, METER SOCKETS ARE FURNISHED WITH A HUB SIZED AS NEEDED; AVAILABLE HUB SIZES ARE 1-1/4", 1-1/2", 2" AND 2-1/2" .



**REQUIREMENTS & STANDARDS
METER SOCKET UP TO 400 AMP
WIRING DIAGRAM
3 WIRE WYE 1 PHASE
120/240 OR 277/480 VOLT
(5 TERMINAL SOCKET W/ LINK BY-PASS)**

DWG: **6.1.2**

REV. 0.00

BY: GWK/BT

DATE: 3/30/17